



Technical Documentation for China GB 43630-2023 “Energy Efficiency Minimum Allowable Values and Grades for Tower and Racker Servers”

Oracle America Inc.
500 Oracle Parkway
Redwood Shores, CA 94065 USA
www.oracle.com

Product Type	Resilient Server
Name/Address of Manufacturer	Oracle America Inc...
Product Model Number	T8-2 Server, all models as defined in the DoC
Compliance Model Number	T82
Year of Manufacture	2017
PSU Efficiency	10% Load: 85.80%
	20% Load: 90.76%
	50% Load: 92.10%
	100% Load: 89.86%
Power Factor at 50% load	1.00
Power Supply rated power output	2013W
Idle State Power	Tested single configuration: T8-2 2Socket, 16x 16GB DIMMS, 1x HDD, 0 PCIE Cards, 2x PSUs. 1030 Watts @ 22 DegC
Maximum Measured Power	http://www.oracle.com/us/products/servers-storage/sun-power-calculators/index.html
Declared Operating Condition Class	A2
Idle power consumption at high boundary of declared operating condition	Tested single configuration: T8-2 2Socket, 16x 16GB DIMMS, 1x HDD, 0 PCIE Cards, 2x PSUs. 1113 Watts @ 35 DegC
Active State Efficiency	Exempt
Products disassembly for service	Oracle products are designed to be readily disassembled for Service. See product Service Manual for details.
Content of Cobalt in batteries and Neodymium in HDDs	Cobalt weight is less than 5g Neodymium Content HDDs with a capacity of 1.2G, 8TB and 10TB fall within 5g & 25g HDDs with a capacity of 14TB are less than 5g.



Technical Documentation for China GB 43630-2023 “Energy Efficiency Minimum Allowable Values and Grades for Tower and Racker Servers”

Oracle America Inc.
500 Oracle Parkway
Redwood Shores, CA 94065 USA
www.oracle.com

Secure deletion functionality

See Note 1

Note 1:

Oracle provides as a part of its Operating System (Oracle Linux, and Solaris) an interface to send commands to attached storage devices. This interface permits issuing commands to trigger secure data deletion

All Oracle storage devices respond to the Operating system commands in any one of the following ways, to comply with the 'secure data deletion' requirement.

1. Overwriting all User blocks of data using write commands
2. Sanitize command - removing reference to User data blocks
3. Key deletion command- Changing encryption keys

In cases where Overwrite of the specific block is either not possible or not supported, Sanitize & key deletion will be used to accomplish the secure deletion intent of the regulation.

The link for China NDRC CEL 046-2025 for “Catalog of Products Subject to the Energy Efficiency Label (17th Batch):

https://www.ndrc.gov.cn/xxgk/jd/jd/202501/t20250124_1395890.html

<https://www.ndrc.gov.cn/xxgk/zcfb/ghxwj/202501/P020250123335750401178.pdf>